



**Bushel Plus**

# MAD Concaves Configuration & Settings Guide for John Deere

Crop	Wheat	Barley/Oats	Soybeans	Canola	Flax	Peas
<b>Rotor</b>	1000	800	550	500/600	1000	450
<b>Fan</b>	1050	1020	1050	850	750	1050
<b>Concave</b>	5	15	10	15	0	15
<b>Top Sieve</b>	18	18	18	15	6	18
<b>Bottom Sieve</b>	7	10	10	4-5	6	11
<b>1st Position Concave</b>	.225	.375/Finger	.375/Finger	.375/Finger	.225	Finger
<b>2nd Position Concave</b>	.375	.375/Finger	.375	.375/Finger	.375	Slot/.375
<b>3rd Position Concave</b>	One Piece .437	One Piece .437	One Piece .437	One Piece .437	One Piece .437	One Piece .437

\*In dry canola conditions, use finger grates in the 1st position.

☎ 1.833.376.7726  
1.204.717.0796

📍 Brandon MB, Canada  
🌐 [www.BushelPlus.com](http://www.BushelPlus.com)